



GM-8FX : 8 Channel Mixer (4 Mono / 2 Stereo) with 16 DSP Effect
GM-12FX : 12 Channel Mixer (4 Mono / 4 Stereo) with 16 DSP Effect

TECHNICAL SPECIFICATION

- Insert point on mono input
- 3 band EQ on all input
- 1 Aux send for external effects and monitoring
- Peak LED on all input
- LOW CUT switch on mono input
- MUTE and SOLO switch on all input
- Built in 16 program digital effect
- Voice canceller function
- 7 band graphic EQ
- +48V phantom power supply

MAIN SPECIFICATION :

Channel Mic/Line 8 CH : 4 Mono/2 Stereo [GM-8FX]
 12 CH : 4 Mono/4 Stereo [GM-12FX]

Total Harmonic Distortion $\leq 0.05\%$
 Frequency Response 5Hz-50kHz, +/-3dB
 S/N Ratio $\geq -103\text{dB}$
 Max Output 4V Max
 Input Sensitivity : Mic -60dB
 : Line -40dB
 : Effect Return -40dB
 : Aux in -40dB
 : Tape in -40dB
 Mono Channel EQ : High +/-15dB, 12KHz
 : Mid +/-15dB, 2.5KHz
 : Low +/-15dB, 80Hz
 Stereo Channel EQ : High +/-15dB, 12KHz
 : Mid +/-15dB, 2.5KHz
 : Low +/-15dB, 80Hz
 Power Requirement AC 220V/50Hz

<http://www.nts-solution.com>

All features & specifications are subjected to change without notice.



บริษัท เอ็นทีเอส อิเล็กทรอนิกส์ โซลูชั่น จำกัด
 NTS Electronic Solution Co., Ltd.

1439-1441 ถนนเจริญนคร แขวงบางลำภูล่าง เขตคลองสาน กรุงเทพฯ 10600

โทรศัพท์: 0-2438-7023-4, 0-2437-7639 โทรสาร: 0-2437-1897

<http://www.nts-solution.com> E-mail: nts@nts-solution.com

1439-1441 Charoennakorn Rd. Banglumpoolang Klongsan Bangkok 10600, Thailand

Tel: (+66-2) 438-7023-4, (+66-2) 437-7639 Fax: (+66-2) 437-1897