

H-SERIES

INDOOR / OUTDOOR SET-UP LOUDSPEAKER

NTS



TECHNICAL SPECIFICATION

■ H-3 / H-3T

| | |
|------------------------------------|-------------------|
| Rated power | 15W RMS |
| Power [MAX] | 25W |
| Bass speaker | 3" |
| Speakers | 0.75" |
| Connections | 2-pole terminal |
| Sensitivity | 83dB |
| Impedance | 8Ω |
| Frequency-range | 100Hz ~ 18KHz |
| Dimension [HxWxD] | 165x115x165 mm. |
| H-3T Line Transformer | 2/4/8/12 W (100V) |

■ H-5 / H-5T

| | |
|------------------------------------|-------------------|
| Rated power | 35W RMS |
| Power [MAX] | 75W |
| Bass speaker | 5" |
| Speakers | 1" |
| Connections | 2-pole terminal |
| Sensitivity | 89dB |
| Impedance | 8Ω |
| Frequency-range | 60Hz ~ 20KHz |
| Dimension [HxWxD] | 256x167x218 mm. |
| H-5T Line Transformer | 2/4/8/16 W (100V) |

■ H-8 / H-8T

| | |
|------------------------------------|--------------------|
| Rated power | 85W RMS |
| Power [MAX] | 125W |
| Bass speaker | 8" |
| Speakers | 1" |
| Connections | 2-pole terminal |
| Sensitivity | 90dB |
| Impedance | 8Ω |
| Frequency-range | 45Hz ~ 20KHz |
| Dimension [HxWxD] | 360x240x254 mm. |
| H-8T Line Transformer | 4/8/16/30 W (100V) |

<http://www.nts-solution.com>

All features & specifications are subjected to change without notice.

NTS

บริษัท เอ็นทีเอส อิเล็กทรอนิกส์ โซลูชั่น จำกัด
NTS Electronic Solution Co., Ltd.

1439-1441 ถนนเจริญนคร แขวงบางลำภูล่าง เขตคลองสาน กรุงเทพฯ 10600

โทรศัพท์: 0-2438-7023-4, 0-2437-7639 โทรสาร: 0-2437-1897

<http://www.nts-solution.com> E-mail: nts@nts-solution.com

1439-1441 Charoennakorn Rd. Banglumpoolang Klongsan Bangkok 10600, Thailand

Tel: (+66-2) 438-7023-4, (+66-2) 437-7639 Fax: (+66-2) 437-1897