

SMR-SERIES

STEREO MIXER WITH 16 DSP EFFECT & USB



SMR6 : 6 Channel Mixer (2 Mono / 2 Stereo)

SMR8 : 8 Channel Mixer (4 Mono / 2 Stereo)

TECHNICAL SPECIFICATION

- 3 band EQ on mono input
- 2 band EQ on stereo input
- 1 Aux send for external effects and monitoring
- Peak LED on all input
- Built in 16 program digital effect
- USB interface for MP3 input and playback
- +48V phantom power supply

Input Channel

Channel Mic/Line 6 CH : 2 Mono/2 Stereo [SMR6]
 8 CH : 4 Mono/2 Stereo [SMR8]
 Mic Input Electronically balanced
 : Frequency Response 10Hz to 200KHz
 : Gain Range +14dB to +60dB
 : SNR 120dB E.I.N.
 Line Input Electronically balanced
 : Frequency Response 10Hz to 130KHz
 : Gain Range -6dB to +38dB
 : SNR 95dB E.I.N.

Stereo Channel

Frequency Response 10Hz to 70KHz
 Gain Range : Line -8dB to +15dB
 : Mic +13dB to +60dB
 SNR : Line 96dB
 : Mic 104dB E.I.N.

Equalization

Mono Channel EQ : High +/-15dB, 12KHz
 : Mid +/-15dB, 2.5KHz
 : Low +/-15dB, 80Hz
 Stereo Channel EQ : High +/-15dB, 10KHz
 : Low +/-15dB, 120Hz

Main Mix

Main Output +28dBu balanced / +22dBu unbalanced
 AUX Send +22dBu unbalanced
 Tape Out +22dBu unbalanced
 Phone Output +15dBu

Physical Dimension and Weight

Dimension [HxWxD] 72 x 210 x 250 mm. [SMR6]
 72 x 260 x 250 mm. [SMR8]
 Weight 3.0 kg. [SMR6]
 3.7 kg. [SMR8]

<http://www.nts-solution.com>

All features & specifications are subjected to change without notice.

NTS บริษัท เอ็นทีเอส อิเล็กทรอนิกส์ โซลูชั่น จำกัด
 NTS Electronic Solution Co., Ltd.

1439-1441 ถนนเจริญนคร แขวงบางลำภูล่าง เขตคลองสาน กรุงเทพฯ 10600

โทรศัพท์: 0-2438-7023-4, 0-2437-7639 โทรสาร: 0-2437-1897

<http://www.nts-solution.com> E-mail: nts@nts-solution.com

1439-1441 Charoennakorn Rd. Banglumpoolang Klongsan Bangkok 10600, Thailand

Tel: (+66-2) 438-7023-4, (+66-2) 437-7639 Fax: (+66-2) 437-1897