

# FS-SERIES

STEREO MIXER with EFFECT / USB / BLUETOOTH

# NTS



**FS-10** : 10 Channel Mixer (6 Mono / 2 Stereo) with 99 DSP Effect

**FS-12** : 12 Channel Mixer (8 Mono / 2 Stereo) with 99 DSP Effect

## TECHNICAL SPECIFICATION

- Insert point on mono input
- 3 band EQ on all input
- 1 Aux send for external effects and monitoring
- Peak LED on all input
- LOW CUT switch on mono input
- MUTE switch on all input
- Built in 99 program digital effect
- USB interface for MP3 input and playback with digital display
- BLUETOOTH function
- 7 band graphic EQ
- +48V phantom power supply

### MAIN SPECIFICATION :

Channel Mic/Line ..... 10 CH : 6 Mono/2 Stereo [FS-10]  
..... 12 CH : 8 Mono/2 Stereo [FS-12]

Total Harmonic Distortion ..... 0.01%

Frequency Response ..... 10Hz-60kHz, +/-3dB

S/N Ratio ..... 112dB

Max Output ..... 22dBu balanced

Aux Send Max Output ..... 22dBu unbalanced

Control Room Output ..... 22 dBu unbalanced

Equalization : High ..... +/-15dB, 12KHz  
: Mid ..... +/-15dB, 2.5KHz  
: Low ..... +/-15dB, 80Hz

Power Requirement ..... AC 220V/50Hz

<http://www.nts-solution.com>

All features & specifications are subjected to change without notice.

# NTS

บริษัท เอ็นทีเอส อิเล็กทรอนิกส์ โซลูชั่น จำกัด  
NTS Electronic Solution Co., Ltd.

1439-1441 ถนนเจริญนคร แขวงบางลำภูล่าง เขตคลองสาน กรุงเทพฯ 10600

โทรศัพท์: 0-2438-7023-4, 0-2437-7639 โทรสาร: 0-2437-1897

<http://www.nts-solution.com> E-mail: [nts@nts-solution.com](mailto:nts@nts-solution.com)

1439-1441 Charoennakorn Rd. Banglumpoolang Klongsan Bangkok 10600, Thailand

Tel: (+66-2) 438-7023-4, (+66-2) 437-7639 Fax: (+66-2) 437-1897